
User Guide

Vandal proof pictogram with emergency light – Surface mounted. Round cable



Package Content

- Pictogram with emergency light
- USB-C to JST SR connector
- Extra 3M™ VHB™ adhesive
- 10 cm USB-C cable
- 3-meter JST SR cable
- 3M™ VHB™ Surface Cleaner
- 3 pcs. 2.4x10mm Aluminum Blind Rivet

Tools required

2.5mm twist drill bit for metal.

Technical data

Pictogram

Size (HxWxD): 40 x 60 x 4.2mm + 2.7 x 0.3 x 300mm FFC connection cable

Weight: 28 g

Adhesive 3M VHB + 2 pcs. 2.4 x 10mm blind rivets

Connection cable

Size Ø11 mm x 300cm

Weight: 140 g

Type: USB-C – USB-C

TeleTech 

User Guide

Pictogram with emergency light– Surface mounted.

General Information

This unit has been constructed using state-of-the-art technology and in compliance with recognized safety standards. The installation instructions contained in this manual must be followed by all personnel involved in the installation and maintenance of the unit. It is crucial that these instructions are made available to the relevant technicians, engineers, and maintenance staff.

To ensure safe handling and trouble-free operation of the system, it is essential to have a thorough understanding of the basic and special safety regulations applicable to conveyor technology and elevators. The unit should only be used for its intended purpose and no unauthorized modifications or additions should be made to it.

TeleTech assumes no liability for damage, loss, or costs resulting from accidents, misuse, incorrect installation, or unauthorized modifications, repairs, or additions to the product. Claims under warranty are also excluded in such cases.

Important safety precautions must be observed when installing and configuring this product. Only authorized and trained professionals should perform these tasks, and the equipment should be used solely for its intended purpose. Before returning the equipment to normal use, it should be fully tested to ensure correct operation. Electrical and electronic components in this product may contain materials that are hazardous to the environment and human health. Please consult local regulations for proper disposal of the old product to prevent negative environmental and health impacts.

Recycle

Always return your used electronic products, batteries, and packaging material to dedicated collection points. This way you help prevent uncontrolled waste disposal and promote the recycling of materials. All materials of the device can be recovered as materials and energy. The crossed-out wheeled-bin symbol on the alarm indicates that all electrical products must be taken to separate collection at the end of their working life.

Safety.

- Keep the device dry. Precipitation and all types of liquids can contain minerals that corrode electronic circuits.
- Do not open the device other than as instructed in this user guide.
- Unauthorized modifications may damage the device.
- Do not drop, knock, or shake the device.
- Only use a soft, clean dry cloth to clean the surface of the device.
- Do not paint the device. Paint can prevent proper operations.
- When you disconnect any cables from the device, hold and pull the plug, not the cord.

Installation

1. Select a Suitable Location Choose an appropriate spot for installing the pictogram.
2. Drill the Mounting Hole Drill a hole with a minimum diameter of 6.5 mm at the center of the chosen location.
3. Clean the Surface Thoroughly clean the area to remove any oil, grease, or other contaminants using the supplied 3M™ VHB™ Surface Cleaner.
4. Install the Cable Attach the cable to the pictogram and feed it through the drilled hole.
5. Mount the Pictogram Remove the protective plastic from the adhesive backing. Press the pictogram firmly into place and hold it for 10 seconds to ensure optimal adhesion.
6. Use a 2.5mm drill bit for metal, and drill 2 holes using the predrilled holes in the pictogram as a guide.
7. Fasten the pictogram to the wall of the lift using the 2 blind rivets.
8. Connect to the Alarm Route the cable to the alarm unit. Insert the plug into the connector and connect it to the alarm using the USB-C plug.

! Fasten the cable so there is no strain on the JST-SR cable.

TeleTech

TeleTech A/S

www.abp-teletech.com

info@abp-teletech.com